

INTERNATIONAL ELECTROTECHNICAL COMMISSION **IEC Certification System for Explosive Atmospheres**

for rules and details of the IECEx Scheme visit www.iecex.com

Certificate No.: **IECEx ULD 16.0022X** Page 1 of 4

Issue No: 3 Status: Current

2020-01-27 Date of Issue:

Applicant: Intelligent Platforms LLC

2500 Austin Drive Charlottesville, VA 22911 **United States of America**

Equipment: Interface modules, Open Type Programmable Controllers - Series EP u-remote

Optional accessory:

Type of Protection: Non-sparking "nA", Encapsulated "nC"

Marking: Ex nA IIC T4 Gc

Ex nA nC IIC T4 Gc (Model EP-2714 only)

-20°C to +60°C

Approved for issue on behalf of the IECEx Katy A. Holdredge

Certification Body:

Position: Senior Staff Engineer

Signature:

(for printed version)

(for printed version)

- This certificate and schedule may only be reproduced in full.
 This certificate is not transferable and remains the property of the issuing body.
 The Status and authenticity of this certificate may be verified by visiting www.iecex.com or use of this QR Code.

Certificate issued by:

UL International DEMKO A/S Borupvang 5A DK-2750 Ballerup **Denmark**



Certificate history: Issue 2 (2018-03-13)

Issue 1 (2017-11-30) Issue 0 (2016-07-27)





Certificate No.: IECEx ULD 16.0022X Page 2 of 4

Date of issue: 2020-01-27 Issue No: 3

Manufacturer: Intelligent Platforms LLC

2500 Austin Drive Charlottesville, VA 22911 United States of America

Manufacturing locations:

This certificate is issued as verification that a sample(s), representative of production, was assessed and tested and found to comply with the IEC Standard list below and that the manufacturer's quality system, relating to the Ex products covered by this certificate, was assessed and found to comply with the IECEx Quality system requirements. This certificate is granted subject to the conditions as set out in IECEx Scheme Rules, IECEx 02 and Operational Documents as amended

STANDARDS:

The equipment and any acceptable variations to it specified in the schedule of this certificate and the identified documents, was found to comply with the following standards

IEC 60079-0:2011 Explosive atmospheres - Part 0: General requirements

Edition:6.0

IEC 60079-15:2010 Explosive atmospheres - Part 15: Equipment protection by type of protection "n"

Edition:4

This Certificate **does not** indicate compliance with safety and performance requirements other than those expressly included in the Standards listed above.

TEST & ASSESSMENT REPORTS:

A sample(s) of the equipment listed has successfully met the examination and test requirements as recorded in:

Test Report:

DK/ULD/ExTR16.0022/03

Quality Assessment Reports:

GB/FME/QAR19.0017/00 NL/DEK/QAR12.0052/06



Certificate No.: IECEx ULD 16.0022X Page 3 of 4

Date of issue: 2020-01-27 Issue No: 3

EQUIPMENT:

Equipment and systems covered by this Certificate are as follows:

The Interface modules, Open Type Programmable Controllers – Series EP u-remote modules are intended to be used in combination with programmable controllers and intended to be used for communication and input / output purposes. The system consists of Bus Coupler Modules and Input / Output Modules with different functions.

The Input and Output Modules are consisting of a base module with connections to the communication bus and power sources, different electronic modules and a modular terminal block module.

Please see Annex for additional information.

SPECIFIC CONDITIONS OF USE: YES as shown below:

- The equipment shall be installed in an enclosure that provides a degree of protection not less than IP 54 in accordance with IEC 60079-15, accessible only by the use of a tool.
- The equipment shall only be used in an area of not more than pollution degree 2, as defined in IEC 60664-1.
- When using relay modules (EP-2714; EP-2814) in explosive atmosphere. Transient protection shall be provided that is set at a level not exceeding 140 % of the peak rated voltage value at the supply terminals to the equipment.



Certificate No.: IECEx ULD 16.0022X Page 4 of 4

Date of issue: 2020-01-27 Issue No: 3

DETAILS OF CERTIFICATE CHANGES (for issues 1 and above)

Issue 1: Model EPXMBE101 was added to the certificate.

Issue 2: The following models were added: EP-3368, EP-3468, EP-5261, EP-1804, EP-5311.

Issue 3: Company name change. Additional models EP-3F68, EP-3664, EPXPNS101, EPXEIP001, EP-153F, EP-2924, EP-291F, EP-12F2, and EP-5324 added.

Annex:

Annex to IECEx ULD 16.0022X Issue 3.pdf



Certificate No.: IECEx ULD 16.0022X

Issue No.: 3 Page 1 of 15

TYPE DESIGNATION

Models:

EP-1214, EP-1218, EP-125F, EP-2214, EP-2614, EP-2218, EP-225F, EP-2714, EP-5111, EP-5112, EP-5422, EP-5442, EP-3164, EP-4164, EP-3704, EP-3804, EP-8310, EP-7631, EP-7641, EP-711F, EP-751F, EP-700F, EP-710F, EP-750F, EPXPBS001, EPXPNS001, EPXMBE001, EPXETC001, EP-1901, EP-1922, EP-1902, EP-3124, EP-1318, EP-12F4, EP-2634, EP-2814, EP-5212, EP-3264, EP-3368, EP-3468, EP-3F68, EP-4264, EP-5261, EP-1804, EP-5311, EPXMBE101, EP-8400, EP-3664, EPXPNS101, EPXEIP001, EP-153F, EP-2924, EP-291F, EP-5324.

Model	Туре	Main Input	Auxiliary Input / Output
EPXPNS001 EPXPNS101	Bus Coupler ProfiNet IRT	Input voltage I port: DC 24V	Output voltage system bus: 5Vdc +/-2%
LF XF NOTOT	FIOIINELIIVI		
		Input current at I port at full load: <=10A	Output current at system bus at full load:2.56A
			Output / input current at O / I Port
		Input voltage O port: DC 24V	at full load: 24Vdc, 10A at 55°C, 8A at 60°C
		Input current at O port at full load: <=10A	
EPXETC001	Bus Coupler EtherCat	Input voltage I port: DC 24V	Output voltage system bus: 5Vdc +/-2%
		Input current at I port at full load: <=10A	Output current at system bus at full load: 2.56A
		Input voltage O port: DC 24V	Output / input current at O / I Port at full load: 24Vdc, 10A at 55°C, 8A at 60°C
		Input current at O port at full load: <=10A	,
EPXMBE001	Bus Coupler ModBus TCP	Input voltage I port: DC 24V	Output voltage system bus: 5Vdc +/-2%
		Input current at I port at full load: <=10A	Output current at system bus at full load: 2.56A
		Input voltage O port: DC 24V	Output / input current at O / I Port at full load: 24Vdc, 10A at 55°C, 8A at 60°C
		Input current at O port at full load: <=10A	217 do, 107 dt 00 0, 07 dt 00 0



Certificate No.: IECEx ULD 16.0022X

Issue No.: 3 Page 2 of 15

Model	Туре	Main Input	Auxiliary Input / Output
EPXPBS001	Bus Coupler Profibus DP	Input voltage I port: DC 24V	Output voltage system bus: 5Vdc +/-2%
		Input current at I port at full load: <=10A	Output current at system bus at full load: 2.56A
		Input voltage O port: DC 24V	Output / input current at O / I Port at full load: 24Vdc, 10A at 55°C, 8A at 60°C
		Input current at O port at full load: <=10A	
EP-1214	2 or 4 Digital Inputs	rated voltage: 24V DC	rated voltage:
EP-12F4	приз	from internal I bus	24V DC
			sensor supply:
			24Vdc, 2A resistive maximum per sensor, unfused
EP-125F EP-153F	16 Digital Inputs	rated voltage: 24V DC from internal I bus	rated voltage:
EP-2214	4 Digital Outputs	rated voltage: 24V DC from internal O bus	24V DC rated voltage: 24V DC output current (DO): 0.5A resistive maximum per output sensor supply (auxiliary 24VDC): 2A maximum per sensor, unfused
EP-2218	8 Digital Outputs	rated voltage: 24V DC from internal O bus	rated voltage: 24V DC output current: 24Vdc, 0.5A resistive or tungsten maximum per output
EP-2614 EP-2924	4 Digital Outputs	rated voltage: 24V DC from internal O bus	rated voltage: 24V DC output current (DO): 2A resistive or tungsten maximum per output sensor supply (auxiliary 24VDC): 2A maximum per sensor, unfused Total current: 10A per module
EP-2218	8 Digital Outputs	rated voltage: 24V DC from internal O bus	rated voltage: 24V DC output current: 24Vdc, 0.5A resistive or tungsten maximum per output



Certificate No.: IECEx ULD 16.0022X

Issue No.: 3 Page 3 of 15

Model	Туре	Main Input	Auxiliary Input / Output
EP-225F EP-291F	16 Digital Outputs	rated voltage: 24V DC from internal bus	rated voltage: 24V DC output current: 24Vdc, 0.5A resistive or tungsten maximum per output
EP-2714	4 Relay Outputs	rated voltage: 24V DC from internal O bus	rated voltage: 250Vac rated current: 2.4A per channel at 60°C and 3A per channel at 55°C
EP-3164 EP-3124	4 Analog Inputs	rated voltage: 24V DC from internal I bus	type of input: analog +/-10V, +/-5V, 010V, 05V, 210V, 15V, 020mA or 420mA
			sensor supply: 24Vdc, 2A maximum per sensor, unfused, 0.5A for HD version, fused
EP-3F68	8 Analog Inputs	rated voltage: 24V DC from the 4 pole terminal block of the module	type of input: analog 020mA or 420mA sensor supply: 24Vdc, 1A maximum, fused
EP-4164 EP4264	4 Analog Outputs	rated voltage: 24V DC from internal O bus	type of output: analog +/-10V, +/-5V, 010V, 05V, 210V, 15V, 020mA or 420mA
EP-3264	4 Analog Inputs	rated voltage: 24V DC from internal I bus	type of input: analog +/-10V, +/-5V, 010V, 05V, 210V, 15V, 020mA or 420mA sensor supply:
EP-3704	4 Analog Inputs Resistive Temperature Detection	rated voltage: 24V DC from internal I bus	24Vdc, 0.5A fused type of input: analog Pt100, Pt200, Pt500, Pt1000, Ni100, Ni120, Ni 200, Ni500, Ni1000, Cu10, 40 Ω, 80 Ω, 150 Ω, 300 Ω, 500 Ω, 1 kΩ, 2 kΩ, 4 kΩ
EP-3804	4 Analog Inputs Thermocouple	rated voltage: 24V DC from internal I bus	type of input: analog TC type J, K, T, B, N, E, R, S, L, U, C, mV +/-15.625mV, +/-31.25mV, +/- 62.5mV, +/-125mV +/-250mV, 500mV, +/-1000mV, +/-2000mV



Certificate No.: IECEx ULD 16.0022X

Issue No.: 3 Page 4 of 15

Model	Туре	Main Input	Auxiliary Input / Output
EP-7631	Power Feed	rated voltage:	rated voltage:
	Input	24V DC from 4 pole	24V DC
	,	terminal block	
			rated current:
			10A
EP-7641	Power Feed	rated voltage:	rated voltage:
	Output	24V DC from the 4 pole	24V DC
		terminal block	
			rated current:
			10A
EP-710F	Potential	rated voltage:	0V / GND
	Distribution	24V DC from internal I	rated current:
EP-711F	Module for	bus	10A
	Input Current		
EP-8310	Path		
EP-750F	Potential	rated voltage:	0V / GND
2. 700.	Distribution	24V DC from internal O	rated current:
EP-751F	Module for	bus	10A
2	Output		10,1
EP-700F	Current Path		
EP-1318	8 Digital	rated voltage:	rated voltage:
2	Inputs	24V DC from internal I	24V DC
EP-1218	in para	bus	
21 1210			sensor supply:
			24Vdc, 2A maximum per sensor
			unfused,
			HD version FWT 1 to 4: 0.5A
			maximum total current, FWT 5 to
			8: 0.5A maximum total current
EP-5212	Counter with	rated voltage: 24V DC	rated voltage:
LI OZIZ	or without	from internal I bus	24V DC
EP-5111	digital output	Trom internal i bus	247 00
LI OIII	aigitai oatpat		output current 1CNT-1DO:
EP-5112			0.5A resistive maximum per
LI OTTE			output
			Catput
			sensor supply:
			24Vdc , 2A maximum per sensor
			unfused
EP-5422	Pulse Width	rated voltage: 24V DC	rated voltage:
21 0122	Controller with	from internal O bus	24V DC
EP-5442	0.5A or 2A	mom memar o bao	211 30
LI OTTE	output		output current:
	output		0.5(forPN-0.5A models)
			0.0(101 14 0.0/(11100013)
			2A (forPN-2A models) resistive
			maximum per output
			maximum per output
			sensor supply:
			24Vdc, 2A maximum per sensor
			unfused
			uniusea



Certificate No.: IECEx ULD 16.0022X

Issue No.: 3 Page 5 of 15

Model	Type	Main Input	Auxilian/Input / Output
Model EP-2634	Type	Main Input	Auxiliary Input / Output
EP-2634	4 Digital	rated voltage: 24V DC	rated voltage:
	Outputs	from internal O bus	24V DC
			and an arrange
			output current:
			2A resistive or tungsten
			maximum per output
			sensor supply:
			24Vdc , 2A maximum per sensor,
			unfused
			total current per module: 10A
			maximum
EP-2814	4 Solid State		rated voltage:
	Relay Outputs		24V DC
			SSR rated voltage:
			250Vac
			SSR rated current:
			1A resistive maximum per
	<u> </u>		channel, unfused
EP-1901	Power Feed	rated voltage:	rated voltage:
	Output	24V DC from the 4 pole	24V DC
EP-1902		terminal block of the	
		module	rated current:
EP-1922			OSSD: 8A resistive
			SSI: 0.5A resistive
EPXMBE101	Bus Coupler	Input voltage I port: DC	Output voltage system bus:
	Modbus / TCP	24V	5Vdc +/-2%
		Input current at I port	Output current at system bus at
		at full	full
		load: <=10A	load:
		1044. \=10/4	2.56A
		Input voltage O port: DC	
		24V	Output / input current at O / I Port
			at
		Input current at O port	full load:
		at full	8A at 60°C, horizontal mounting,
		load: <=10A	6A
		10au. <=10A	at 55°C, vertical mounting



Certificate No.: IECEx ULD 16.0022X

Issue No.: 3 Page 6 of 15

Madal	T	Main Innut	Association states to the terminal of the term
Model	Туре	Main Input	Auxiliary Input / Output
EPXEIP001	Bus Coupler Ethernet IP	Input voltage I port: DC 24V	Output voltage system bus: 5Vdc +/-2%
		Input current at I port at full load: <=10A	Output current at system bus at full load: 2.56A
		Input voltage O port: DC 24V	Output / input current at O / I Port at full load: 24Vdc, 10A at 55°C, 8A at 60°C
		Input current at O port at full load: <=10A	
EP-3368 EP-3468	8 Analog Inputs	rated voltage: 24V DC from internal I bus	type of input: analog +/-10V, +/-5V, 010V, 05V, 210V, 15V, 020mA or 420mA
			sensor supply: 24Vdc 2A maximum per sensor, unfused, 0.5A for HD version, fused
EP-5261	1 Port Digital Interface	rated voltage: 24 V DC from internal I bus	Data interface signal: 232, 485 or 422
			Load sensor supply: 0.4A (5V) or 0.5A (24V)
EP-1804	4 Digital Inputs	rated voltage: 24 V	Rated input voltage: 230V AC
EP-5311	1 Port Inout Card for Incremental Encoder	rated voltage: 24V DC from internal I bus	1 RS422 Output 2 RS422 Input
EP-3664	Al Module 4 analog inputs	5Vdc system bus 24V DC from internal I bus	Voltage: 05V, ±5V, 010V, ±10V, 15V, 210V Current: 020mA, 420mA
EP-5324	Comm. Module	5Vdc system bus 24V DC from internal I bus	0,5 A per channel, total max. 2 A




Certificate No.: IECEx ULD 16.0022X

Issue No.: 3 Page 7 of 15

Model	Туре	Main Input	Auxiliary Input / Output
EPXPBS001	Bus Coupler Profibus DP	Input voltage I port: DC 24V Input current at I port at full load: <=10A Input voltage O port: DC 24V Input current at O port at full load: <=10A	Output voltage system bus: 5Vdc +/-2% Output current at system bus at full load: 2.56A Output / input current at O / I Port at full load: 24Vdc, 10A at 55°C, 8A at 60°C
EP-5261	1 Port Digital Interface	rated voltage: 24 V DC from internal I bus	Data interface signal: 232, 485 or 422 Load sensor supply: 0.4A (5V) or 0.5A (24V)

MARKING


Marking has to be readable and indelible; it has to include the following indications:





Certificate No.: IECEx ULD 16.0022X


Issue No.: 3 Page 8 of 15





Certificate No.: IECEx ULD 16.0022X


Issue No.: 3 Page 9 of 15





Certificate No.: IECEx ULD 16.0022X


Issue No.: 3 Page 10 of 15





Certificate No.: IECEx ULD 16.0022X


Issue No.: 3 Page 11 of 15





Certificate No.: IECEx ULD 16.0022X


Issue No.: 3 Page 12 of 15





Certificate No.: IECEx ULD 16.0022X


Issue No.: 3 Page 13 of 15





Certificate No.: IECEx ULD 16.0022X

Issue No.: 3 Page 14 of 15





Certificate No.: IECEx ULD 16.0022X

Issue No.: 3 Page 15 of 15

